Brain Machine kit

Assembly Instructions
& Programming Instructions










Brain Machine kit



Disclaimer:

Light and Sound Machines, such as this one, can be fun for many of us, but may be seriously dangerous for those prone to seizures or who are photosensitive.




The following photos will show you how to solder.

But feel free to download the "Soldering Is Easy" comic book for free!


(In many different languages.)

http://mightyohm.com/soldercomic download for free at:

Learn To Solder



Learn To Solder



earn To Solder





Learn To Solder




Learn To Solder











The board we'll solder the parts to



Front/Top of board



Back/Bottom of board



- soldering Iron (35W or less)
- solder (more details coming)
- soldering iron stand
- cellulose kitchen sponge (not plastic!)

- tape
- felt-tip pen


Our first part



(not: Yellow, Violet, Black)




Some parts, such as resistors, need their leads bent first







R1 – this is how it will look *before* inserting it into the board




R1 – this is where it goes


R1







so that the part won't fall out while soldering it



R1 – inserted into the board



How to hold a soldering iron

(Like a pencil – held from underneath)



The best kind of solder for DIY electronics:

(Sn - Tin / Pb - Lead)

(60/A0 is also 9000) 63/37 rosin core,

0.031" (0.8mm) diameter (or smaller)

Note:

Most

Lead-Free solder has poisonous fumes!

A good kind of solder for DIY electronics:

This is the only good searching)



Kester
K100LD Rosin
(not "No Clean")

0.031" diameter (0.8mm)

A good kind of solder for DIY electronics:

This is the only good searching)



Kester K100LD Rosin Solder

0.031" diameter (0.8mm)


Note:



If you use Lead-Free solder
it is helpful
to also have
flux paste in a syringe
And Isopropyl Alcohol

Another good kind of solder for DIY electronics:

This is another good Lead-Free solder I have found!



Duratool D01685 Rosin

0.7mm diameter

(as good as the Kester K100LD Rosin)

Another good kind of solder for DIY electronics:

This is another good solder I have found!



MG Chemicals 4900 Rosin (112g, 227g, 454g)

0.8mm diameter

(as good as the Kester K100LD Rosin)

3 Safety Tips...

Safety Tip #1:

Hot!!

(When you touch the tip, you will let go quickly every time!)

Safety Tip #2:

Soldering chemicals are toxic

But they easily wash off your hands with soap and water

Safety Tip #3:

(coming soon)

2 secrets to good soldering...


Secret #1:

Clean the tip!


(before every solder connection)

Bang (lightly) 3 times, Swipe, Rotate, Swipe (on the sponge):

Keep the tip shiny silver!




Do this quickly (slowly doesn't work well) – solder in & out in about 1 second




Make sure solder melts on the <u>underside</u> of the soldering iron tip (not the side or top of the soldering iron tip)!

Do this quickly (slowly doesn't work well) – solder in & out in about 1 second





Make sure solder melts on the <u>underside</u> of the soldering iron tip (not the side or top of the soldering iron tip)!



Secret #2:

Keep hot tip down
1 second
for solder to flow!!






If you can see any of the pad, or the hole, you need more solder – so, just do all the steps again to make it perfect.

is just as important as the preceding steps!

The Rhythm! and speed (about 1 second per step)



and speed (about 1 second per step)

Clean the tip



and speed (about 1 second per step)



Tip Down

and speed (about 1 second per step)



Solder In

The Rhythm! and speed (about 1 second per step)



Solder Out

and speed (about 1 second per step)






The Rhythm! and speed (about 1 second per step)






If you are using solder WITH lead (Pb), you can now Solder all of the leads of the part to the board




For this part, there are two leads
Here you can see two good solder connections

Two good solder connections



- Little mountains (not flat)
- Pads totally covered in solder
- Can't see the hole
- No connections to other pads

Now cut the leads short




Cutting with the tip of the wire cutter gives you more control

Safety Tip #3:


Hold or cover the lead!

(or it will fly into your eye!)

(They like doing that – so please hold or cover the lead when you cut.)



No wires sticking out



2 good solder connections


R1 soldered to the board

Notice that:

- Each connection
 is a small mountain
 (not flat)
- You cannot see any pad
 (they're totally covered
 with solder)
- You cannot see the holes (they're totally covered with solder)
- No connections to other pads

One part at a time


Till all the parts are soldered



And it will look like this when you're done soldering.

If you used any flux paste for re-working problems








You can clean it with a cloth wet with Isopropyl Alcohol

Then put in the battery, Turn it on, And it works!

(Or you start debugging.)


Let's start!



If you haven't done so already, solder R1: Yellow, Violet, Red


R1, R2:

R3, R4:




4.7K: Yellow, Violet, Red

47: Yellow, Violet, Black






J1: Headphone Jack




S1: On/Off switch





Pin Headers

long pins



Pin Headers

long pins '

short pins


3 pins


6 pins

9 pins


9 pins

Use wire cutters





Pin Headers for Arduino Nano




long pins sticking up

MPORTANT!

→ Short pins go into the board! ←

→ Do Not solder, yet ←


Arduino Nano placed on its pins




long pins sticking up

→ Short pins go into the board! ←

Arduino Nano soldered to its pins




Arduino Nano soldered to board



Pin Headers for Power Supply

long pins sticking up

MPORTANT!




3 pins

→ Short pins go into the board! ←

→ Do Not solder, yet ←

Power Supply placed on its pins

long pins sticking up




coil


→ IMPORTANT: Power Supply <u>must</u> go in this way! ←
(coil is facing up)

Power Supply soldered to its pins



Power Supply soldered to board





C1, C2


Oirection does not matter

LED1 and LED2:


Red wire


and

Blue wire



LED1, LED2 soldered to board





S1 in OFF position


"+"

""

(spring)




AAA Battery in its holder




Place AAA Battery holder in place

→ <u>Do Not</u> solder, yet ←



Insert Earbuds




Turn ON

- LEDs flicker
- Each ear has a different pitch

If you used any flux paste for re-working problems








You can clean it with a cloth wet with Isopropyl Alcohol

Insert Battery Holder




Battery Holder Soldered




→ <u>DO NOT</u> cut battery holder leads! ←

(That will destroy the wire cutters)




Notice the 4 holes in the board for the zip ties


→ Use left side of glasses ←



Insert zip-ties into lower mounting holes



Wrap zip-ties around, and secure



Cut zip-ties short


Mark where LEDs will go



For each eye:


Slowly move the marker toward your eye to make a mark directly in front of your eye.

LEDs light up on one side



The LEDs light up on the flat white side


Tape Left LED to Glasses



Tape the flat white side of D1 over the left mark


(so the light will shine on your eye)

Tape Right LED to Glasses



Tape the flat white side of D2 over the right mark (so the light will shine on your eye)

Secure LED wires on Glasses




Use tape to clean up and secure the LED wires

Add Trippy Graphics!



Cut out the Trippy Graphics and tape them over the glasses

Done!



Enjoy (with your eyes closed)



Meditate, Hallucinate, Trip Out!

Please Remember:

to
Wash your hands
after soldering

Let's Meditate

Your Brain Machine comes pre-programmed with a really nice 14-minute Meditation.

And, along the way you will hallucinate beautiful colors and patterns from your imagination.





Re-Programming

Your Brain Machine comes pre-programmed with a really nice 14-minute Meditation.

If you are happy with this meditation sequence then no need to re-program your Brain Machine.

But if you want to program other brainwave sequences the next pages show you how...



Re-programming the Brain Machine

We have one other sequence ready for you to use.

It is 1 hour of 40 Hz Gamma Waves

The following slides show you how to program this sequence into your Brain Machine...



Re-programming the Brain Machine

We have one other sequence ready for you to use.

To program in a new sequence into your Brain Machine, you will need:

- the Arduino software
 - http://arduino.cc
- a USB-C cable
- the "sketch" for the other brainwave sequence

http://cornfieldelectronics.com/cfe/projects.php#brainmachine

The following slides show you how to do the above, in detail.



Arduino

Arduino is a very powerful tool!

But it is very easy to use.

It was designed for total beginners to use successfully.

I won't give a complete tutorial here – just some basics.

For more info, there are many good Arduino tutorials online.

A good place to start is:

https://www.arduino.cc/en/Tutorial/HomePage



Arduino

First:

Any version is OK Download and install the Arduino software < http://arduino.cc >



Re-programming the Brain Machine

Second:

Download the Brain Machine brainwave sequence sketch http://cornfieldelectronics.com/cfe/projects.php#brainmachine

Store it on your computer anywhere you like.

(details on this soon)



Connecting your Brain Machine to your computer

USB-C cable




IMPORTANT:
Make sure the
Switch on your
Brain Machine
is OFF

to computer's USB

Connecting your Brain Machine to your computer

USB-C cable



You may need to download and install a driver for your Operating System (Windows, MacOS, or Linux):

or search for:
"CH340 driver"


Arduino

After you download and install the Arduino software start it, and you will see a screen that looks like this:

```
sketch_may1a | Arduino IDE 2.1.0
                                                                                                              File Edit Sketch Tools Help
               Arduino Uno
      sketch_may1a.ino
               void setup() {
                 // put your setup code here, to run once:
           5
              void loop() {
                 // put your main code here, to run repeatedly:
           8
           9
         10
                                                                                       Ln 1, Col 1 Arduino Uno [not connected] 🚨
```

The first time you start your Arduino software you need to set things up

(1)
Choose
"Arduino Nano"
as the Board



The first time you start your Arduino software you need to set things up

(1)
Choose
"Arduino Nano"
as the Board


```
sketch_jan27a | Arduino IDE 2.3.4
File Edit Sketch Tools Help
                                                                                                       √ • ⊙
                sketch_jan27a.ino
             void setup() {
               // put your setup code here, to run once:
         3
         4
             void loop() {
               // put your main code here, to run repeatedly:
         9
        10
                                                        You now see "Arduino Nano"
                                                                           here
(8)
                                                                              Arduino Nano d
                                                                      Ln 1, Col 1
                                                                                          COM11 [not connected] 🚨
```

The first time you start your Arduino software you need to set things up

(2)
Choose
your Processor


"ATmega328P (Old Bootloader)"

If this one doesn't work,
then
choose
"ATmega328P"



The first time you start your Arduino software you need to set things up


(3)
Choose
the Port
(this will be
different
depending on
your Operating
System)



The first time you start your Arduino software you need to set things up

(3)
Choose
the Port
(this will be
different
depending on
your Operating
System)

(After installing
the driver
for your Arduino
(USB-Serial adapter),
with your Arduino
plugged in,
your operating system
will see a serial port
and it appears here.)



The first time you start your Arduino software you need to set things up


Choose
the Port
(this will be
different
depending on
your Operating
System)

(After installing
the driver
for your Arduino
(USB-Serial adapter),
with your Arduino
plugged in,
your operating system
will see a serial port
and it appears here.)

```
sketch_jan27a | Arduino IDE 2.3.4
                                                                                                     File Edit Sketch Tools Help
                Arduino Nano
      sketch jan27a.ino
             void setup() {
               // put your setup code here, to run once:
         3
         4
             void loop() {
              // put your main code here, to run repeatedly:
         9
        10
                                                                      You now see
                                                           "Arduino Nano on COM7"
                                                                            here
(8)
                                                                                         Arduino Nano on COM7
```

Your Arduino software is now ready

to program a new brainwave sequence sketch



Designed for non-geeky artists


Definition of

"Sketch":

an Arduino program

Designed for non-geeky artists

Download the new Gamma "sketch"



"Sketch":


an Arduino program

The following slides show where to find this sketch...

Download a new brainwave sequence "sketch"




Download a new brainwave sequence "sketch"



Download a new brainwave sequence "sketch"




Download a new brainwave sequence "sketch"




Click here to download the Gamma wave sequence sketch


You can now open the brainwave sequence sketch: File → Open...




You can now program your Brain Machine with a new synth sketch!



With the USB-C cable connected to your Brain Machine press the "Upload" button



While uploading, you will see a progress bar...



...and when it's completed successfully, it says: "Upload done"

Brain Machine

Disconnect your Brain Machine board from the USB-C cable,

turn on your Brain Machine,

And...

Let's Trip Out in New Ways!



Please Remember:

to
Wash your hands
after soldering

Brain Machine kit

Assembly Instructions
& Programming Instructions







